

Orthogonality catastrophe in a mesoscopic conductor due to a time-dependent flux.

Hyunwoo Lee, L.S.Levitov*

*Massachusetts Institute of Technology, 12-112, Department of Physics,
77 Massachusetts Ave., Cambridge, MA 02139*

Abstract

We consider quantum fluctuations of current in a metallic loop induced by varying magnetic flux. The dependence of the fluctuations on the flux change Φ contains a logarithmically divergent term periodic in Φ with the period $\Phi_0 = hc/e$. The fluctuation is smallest near $\Phi = n\Phi_0$. The divergence is explained by a comparison with the orthogonality catastrophe problem. The Φ_0 -periodicity is related with the discreteness of "attempts" in the binomial statistics picture of charge fluctuations.

PACS numbers: 72.10.Bg, 73.50.Fq, 73.50.Td

The orthogonality catastrophe problem emerged from the observation that the ground state of a Fermi system with a localized perturbation is orthogonal to the non-perturbed ground state, no matter how weak the perturbation [1]. Originally, the discussion was focused on the purely static effect of Fermi correlations on the ground state that leads to the orthogonality, but then it shifted to dynamical effects. When a sudden localized perturbation is switched on in a Fermi gas, the number of excited particle-hole pairs detected over a large time interval t diverges as $\ln t/\tau$, where τ is the time of switching of the perturbation. This effect leads to power law singularities in transition rates of processes that involve collective response of fermions, e.g., in X-ray absorption in metals [2,3]. In this paper we present an application of the orthogonality catastrophe picture to the theory of quantum noise in electric circuits.

Due to Callen-Welton's theorem, the fluctuations in equilibrium are related in a universal way with kinetic response [4]. However, due to the lack of such relation in the non-equilibrium situation, physics of the non-equilibrium noise may be quite different from that of corresponding kinetic response. In this paper, we study noise in a conductor driven from one equilibrium state to another due to changing flux by a constant amount over fixed time, and find that charge fluctuations distinguish between integer and non-integer flux change in a way resembling Aharonov-Bohm effect. Let us emphasize that the geometry of our conducting loop excludes the usual dc Aharonov-Bohm effect.

Noise in quantum conductors received an increased attention recently due to its relevance for applications and also because it leads to understanding interesting effects in quantum statistics. Initially, only the spectral density of the noise was considered [5,6,7,8,9]; however, it was realized shortly that it is also quite useful to have the picture of charge fluctuations in the time domain, since in the spectral density many important features remain implicit [10]. In particular, the description of the fluctuations in the time domain allows us to approach microscopically the problem of the distribution of charge transmitted through the system over fixed time. This distribution is binomial, i.e., it results from Bernoulli statistics [11]. We discuss below a relation of the binomial distribution with the contribution to the noise periodic in flux.

Let us consider a metallic conductor bent in a loop of length L threaded by a time-dependent magnetic flux (Fig. 1). Ends of the conductor are treated as ideal leads that serve as infinite reservoirs with equilibrium distribution. The flux increases over a time 2τ from zero to a constant value: $\Phi(t \ll -\tau) = 0$, $\Phi(t \gg \tau) = \Phi$. It is assumed that the diffusion picture is valid, i.e., $L \gg l$, the mean free path, and that the time $\tau \gg t_f = 3L^2/v_F l$, the duration of diffusion across the loop. We are interested in fluctuations of the charge Q transmitted through the conductor over a much longer time interval $-t_0 < t < t_0$, $t_0 \gg \tau$. For the transmitted charge $Q = \int_{-t_0}^{t_0} j(t)dt$, we get the expected Ohm's law for the average $\langle Q \rangle = geG_0\Phi/\Phi_0$, where g is spin degeneracy and G_0 is dimensionless conductance expressed through transmission coefficients: $G_0 = \sum_n T_n$, in accordance with Landauer's formula [12]. For the mean square of the charge fluctuation in the limit of low temperature $T \ll \hbar/t_0$ and $\Phi \gg \Phi_0$, we obtain

$$\langle\langle Q^2 \rangle\rangle = ge^2 G_1 \left[\frac{2}{\pi^2} \sin^2 \pi \Phi / \Phi_0 \ln t_0 / \tau + \Phi / \Phi_0 \right] + \dots, \quad (1)$$

where $G_1 = \sum_n T_n(1 - T_n)$. The dots in (1) represent correction higher order in Φ_0/Φ and the equilibrium noise

$$\langle\langle Q^2 \rangle\rangle_{eq} = \frac{ge^2 G_0}{\pi^2} \ln t_0/t_f \quad (2)$$

that follows from the Nyquist formula $\langle\langle j_\omega j_{-\omega} \rangle\rangle = ge^2 G_0 \omega \coth \omega/2T$ taken at $T = 0$, Fourier transformed and combined with the relation $Q = \int_{-t_0}^{t_0} j(t) dt$.

In order to make obvious the mapping on the orthogonality catastrophe problem, let us consider an ideal single channel conductor, i.e., the Schrödinger equation

$$i \frac{\partial}{\partial t} \psi(x, t) = \left[\frac{1}{2} \left(-i \frac{\partial}{\partial x} - \frac{e}{c} A(x, t) \right)^2 + U(x) \right] \psi(x, t)$$

in one dimension, where the potential $U(x)$ represents the scattering region and $A(x, t)$ is the vector potential corresponding to the flux $\Phi(t)$. Since the switching time τ is assumed to be much longer than the transport time t_f , one can treat the vector potential as static and apply a gauge transformation in order to accumulate the flux $\Phi(t)$ in the phases of the transmission amplitudes, thus making them time dependent:

$$A_{L(R)}(t) = A_{L(R)} e^{\pm i\phi(t)} , \quad (3)$$

where $\phi(t) = 2\pi\Phi(t)/\Phi_0$. Then one can write the scattering states with energy close to E_F as

$$\begin{aligned} \psi_{L,k}(x, t) &= e^{-iE_k t} \begin{cases} e^{ikx} + B_L e^{-ikx}, & x < -L/2 \\ A_L(t_r) e^{ikx}, & x > L/2 \end{cases} , \\ \psi_{R,k}(x, t) &= e^{-iE_k t} \begin{cases} A_R(t_r) e^{-ikx}, & x < -L/2 \\ e^{-ikx} + B_R e^{ikx}, & x > L/2 \end{cases} , \end{aligned} \quad (4)$$

where the retarded $t_r = t - |x|/v_F$ takes care of the finite speed of motion after scattering. The effect of the flux on the scattering phases δ_1, δ_2 can be found by diagonalizing the scattering matrix

$$\hat{\mathcal{S}}(t) = \begin{bmatrix} A_L e^{i\phi(t)} & B_R \\ B_L & A_R e^{-i\phi(t)} \end{bmatrix} \quad (5)$$

that has eigenvalues $e^{i\delta_1}, e^{i\delta_2}$. The relation between the phases $\delta_{1,2}$ at $t \ll -\tau$ and their values $\delta'_{1,2}$ at the moment t is written conveniently through $\delta_{\pm} = (\delta_1 \pm \delta_2)/2$:

$$\cos^2 \delta'_+ + \cos^2 \delta'_- - 2 \cos \delta'_+ \cos \delta'_- \cos \phi(t) = |A_L|^2 \sin^2 \phi(t) . \quad (6)$$

Now the situation can be readily understood in terms of the orthogonality catastrophe in the Fermi system with the time dependent perturbation (5). Change of the flux induces the shift of the phases $\delta_{\pm} \rightarrow \delta'_{\pm}$ and makes the new ground state orthogonal to the old one:

$$\langle 0' | 0 \rangle = \exp \left[-2 \frac{\delta^2}{\pi^2} \ln E_F / \Delta \right] , \quad (7)$$

where Δ is level spacing near E_F and $e^{i\delta}$ is an eigenvalue of the matrix $\hat{\mathcal{S}}^{-1}(t) \hat{\mathcal{S}}(t \ll -\tau)$: $\sin \delta/2 = |A_L| \sin \phi(t)/2$. In terms of dynamics this implies that the old ground state

evolves to a state with infinitely many excited particle-hole pairs, in agreement with the standard orthogonality catastrophe calculation [3]. We shall see below that this leads to a logarithmically diverging contribution to noise, since for each of the particle-hole pairs there is a finite probability (equal to $|A_L B_R|^2$) that the particle and the hole will go to different ends of the loop, thus resulting in a current fluctuation. The periodicity in Φ follows from the gauge invariance and is explicit in Expr.(6) for $\delta'_\pm$. The logarithmic divergence vanishes at $\Phi = n\Phi_0$, as should be expected, since at integer Φ there is no long term change of the scattering.

Second term in (1) is interesting in connection with the picture of binomial statistics for the noise at low temperature [11]. In the case of dc bias, the distribution of charge for a single channel situation was found to be binomial with frequency of attempts equal to eV/h and the probabilities of outcomes $p = D$, $q = 1 - D$, $D = |A_L|^2$. If understood literally, this means that the attempts to transfer charge are repeated regularly in time, almost periodic with the period h/eV , with each attempt having two outcomes – transmission or reflection – occurring with the probabilities p and q . However, the regularity of the attempts does not lead to an ac component of current, rather it appears just as a part of statistical description of charge fluctuations. Still, the presence of a non-zero frequency in a non-interacting system requires interpretation.

Let us suppose that the flux varies linearly with time, $\Phi(t) = -cVt$. Because of the expression $-\partial\Phi/c\partial t$ for the e.m.f., the linear dependence of $\Phi(t)$ in its effect on the noise is equivalent to constant voltage V . In accordance with one's expectation, second term of Expr.(1) for a single channel is $\langle\langle Q^2 \rangle\rangle = ge^2 D(1 - D)\Phi/\Phi_0$, i.e., it is precisely of the form arising from the binomial distribution with probabilities of outcomes $p = D$ and $q = 1 - D$ and the number of attempts $N = \Phi/\Phi_0$. (Let us recall that the second moment of the binomial distribution equals pqN .) Taking into account that the time during which the flux changes by Φ_0 is h/eV , we can interpret the number of attempts in the statistical picture as the number of flux quanta by which the flux is changed. Such a conclusion suggests an interesting generalization of the picture of binomial statistics by attributing the meaning of the number of attempts to the flux change measured in units of Φ_0 , regardless of the linear or non-linear character of the flux dependence on time.

Although this picture is yet to be confirmed by analytic treatment, let us remark that it receives some support from the property of the Φ_0 -periodic term in (1) to vanish at integer Φ . One may conjecture that the statistics are purely binomial only when the flux change is an integer and has diverging logarithmic corrections otherwise. The distinction that Expr.(1) makes between integer and non-integer values of the flux and the relation of integer flux change to the number of attempts in the binomial distribution, gives another perspective to the statistical picture of charge fluctuations.

Now let us turn to the calculation. Since the characteristic times we have are longer than $t_f = 3L^2/v_F l$, we can find the fluctuations in one channel and then sum over all conducting channels. Let us start with the time-dependent scattering states (4) and write operators of second quantized electrons as $\hat{\psi}(x, t) = \hat{\psi}_L(x, t) + \hat{\psi}_R(x, t)$, $\hat{\psi}_{L(R)}(x, t) = \sum_k \psi_{L(R),k}(x, t) \hat{a}_{L(R),k}$. Then we write current operator $\hat{j} = -i \frac{e\hbar}{m} \hat{\psi}^+ \nabla \hat{\psi}$ and by averaging $\hat{Q} = \int_{-t_0}^{t_0} \hat{j}(t) dt$ obtain $\langle Q \rangle = geD\Phi/\Phi_0$, consistent with the Ohm's law. Then we compute current-current correlation function $\langle\langle \hat{j}(t_1) \hat{j}(t_2) \rangle\rangle =$

$$\frac{e^2}{h^2} \sum_{E,E'} e^{-i(E-E')(t_1-t_2)} [|A_1 A_2|^2 f_{E,E'}^1 + \bar{B}_1 A_1 \bar{A}_2 B_2 f_{E,E'} + \bar{A}_1 B_1 \bar{B}_2 A_2 f_{E',E}], \quad (8)$$

where $A_{1,2} = A_L(t_{1,2})$, $B_{1,2} = B_R(t_{1,2})$, $f_{E,E'} = n(E')(1 - n(E))$, $f_{E,E'}^1 = f_{E,E'} + f_{E',E}$. To obtain the second moment of charge, we integrate over $-t_0 < t_{1,2} < t_0$, then substitute time dependent scattering amplitudes (3) and $n(E) = (e^{E/T} + 1)^{-1}$. The result reads

$$\langle\langle Q^2 \rangle\rangle = \frac{ge^2}{2\pi} \int [D^2 \left| \int_{-t_0}^{t_0} e^{i\omega t} dt \right|^2 + D(1-D) \left| \int_{-t_0}^{t_0} e^{i\phi(t)+i\omega t} dt \right|^2] \omega \coth \frac{\hbar\omega}{2T} \frac{d\omega}{2\pi}, \quad (9)$$

where $\phi(t) = 2\pi\Phi(t)/\Phi_0$.

The first term in (9) is a part of equilibrium noise since it does not depend on Φ . To analyze the second term, we first look at the step-like time dependence, $\phi(t < 0) = 0$, $\phi(t > 0) = 2\pi\Phi/\Phi_0$, in order to get terms diverging as $t_0 \rightarrow \infty$ and $T = 0$. Thus, we have

$$\frac{ge^2}{2\pi} \int \left| \frac{1 - e^{-i\omega t_0}}{i\omega} + e^{2\pi i\Phi/\Phi_0} \frac{e^{i\omega t_0} - 1}{i\omega} \right|^2 |\omega| \frac{d\omega}{2\pi} = \frac{ge^2}{\pi^2} (1 + 2 \sin^2 \pi\Phi/\Phi_0) \ln \frac{t_0}{t^*}. \quad (10)$$

Logarithmic contribution to the non-equilibrium noise (1) is obtained by subtracting the result for $\Phi = 0$ as corresponding to equilibrium, and then substituting cutoff time $t^* = \tau$.

The term of Expr.(1) proportional to Φ/Φ_0 is obtained by rewriting the second term of (9) as

$$\frac{ge^2}{2\pi} D(1-D) \int \frac{d\omega}{2\pi} |\omega| \int dt_1 \int dt_2 e^{i\phi(t_1) - i\phi(t_2) + i\omega(t_1 - t_2)} \quad (11)$$

and extracting the contribution of almost coinciding times t_1 and t_2 by going to new variables $t = (t_1 + t_2)/2$, $t' = t_1 - t_2$ and changing order of integrations:

$$\int dt \int \frac{d\omega}{2\pi} |\omega| \int dt' e^{i\phi(t+t'/2) - i\phi(t-t'/2) + i\omega t'} = \int |\dot{\phi}| dt, \quad (12)$$

where we replaced $\phi(t+t'/2) - \phi(t-t'/2)$ by $\dot{\phi} t'$. The result (12) is approximate: it does not give the $\log$ term because the transformation (12) properly takes care of the integral (11) only in the domain $t_1 \simeq t_2$, under the restriction that $\Phi(t)$ is varying sufficiently smoothly. When $\Phi(t)$ is a monotonous function, $\dot{\phi} > 0$, the integral in the r.h.s. of (12) equals $2\pi\Phi/\Phi_0$ and thus produces the second term of Expr.(1).

It is clear from the derivation that the two terms of Expr.(1) arise from different integration domains in the $t_1 - t_2$ space: the first term corresponds to $|t_{1,2}| \geq \tau$, $t_1 t_2 < 0$, while the second one is due to almost coinciding moments, $|t_1 - t_2| \ll \tau$. Since the domains are almost non-overlapping, the two contributions to the noise (1) do not interfere (cross terms are small).

In order to have a feeling of how big the correction to Expr.(1) can be, we shall study two examples. Firstly, let us consider functions $\Phi_\alpha(t) = \frac{\alpha}{\pi} \Phi_0 \tan^{-1} t/\tau$ corresponding to $e^{i\phi_\alpha(t)} = ((1 + it/\tau)/(1 - it/\tau))^\alpha$, $\Phi = \alpha\Phi_0$. For integer α Expr.(11) can be evaluated exactly using technique of generating functions. The one useful here is

$$F_\omega(z) = \sum_{n>0} z^n \int e^{i\omega t + i\phi_n(t)} dt = \begin{cases} 0, & \omega > 0 \\ \frac{4\pi z}{(1+z)^2} e^{\omega(1-z)/(1+z)}, & \omega < 0 \end{cases}. \quad (13)$$

The last equality is a result of changing order of summation and integration. Then it is straightforward to compute

$$\int |\omega| F_\omega(z_1) \overline{F_\omega(z_2)} \frac{d\omega}{2\pi} = 2\pi \frac{z_1 \bar{z}_2}{(1 - z_1 \bar{z}_2)^2} . \quad (14)$$

L.h.s. of (14) expanded in series generates integrals (11) for $\phi(t) = \phi_n(t)$ as coefficients of the terms $z_1^n \bar{z}_2^n$. On the other hand, r.h.s. of (14) equals $\sum_{n>0} 2\pi n z_1^n \bar{z}_2^n$. This means that for all $\Phi_n(t)$ Expr.(1) is exact. With this result, we can state that for arbitrary α inaccuracy of Expr.(1) is at most a bounded function of Φ taking zero value at every integer Φ/Φ_0 .

The next function we consider rises linearly in the interval $-\tau < t < \tau$ and is constant for $|t| > \tau$. In this case

$$\int_{-t_0}^{t_0} e^{i\phi(t)+i\omega t} dt = \frac{2}{\omega} e^{\pi i \Phi/\Phi_0} \left[\sin \omega t_0 - \frac{\pi \Phi}{\omega \tau \Phi_0 + \pi \Phi} \sin(\omega \tau + \pi \Phi/\Phi_0) \right] . \quad (15)$$

After substituting this in (9) and subtracting the equilibrium part not vanishing at $\Phi = 0$ one gets

$$ge^2 D(1-D) \int \frac{\Phi^2 \sin^2(\omega \tau + \pi \Phi/\Phi_0)}{(\omega \tau \Phi_0 + \pi \Phi)^2 |\omega|} d\omega . \quad (16)$$

The integral is converging for $\Phi = n\Phi_0$ and logarithmically diverging otherwise, as it should be. For large integer n one easily evaluates it using the expansion

$$\int_{-\infty}^{\infty} \frac{\sin^2 x}{(x + \pi n)^2 |x|} dx = \frac{1}{n} + \frac{\ln n}{\pi^2 n^2} + O(n^{-2}) , \quad (17)$$

and obtains correction to Expr.(1):

$$\frac{ge^2}{\pi^2} D(1-D) \ln \Phi/\Phi_0 \quad (18)$$

plus higher order terms. As one might have expected, the noise comes to be stronger for our second function since it is less smooth. However, the correction (20) is relatively small, even for it.

At this point let us recall that in order to generalize our results for a single channel to the case of a mesoscopic conductor containing many conducting channels, one just needs to replace $D(1-D)$ by $\sum_n T_n(1-T_n)$. The condition of validity of our treatment then is $\tau \gg 3L^2/v_F l = \hbar/E_c$, the time of diffusion across the sample.

Let us discuss the possibilities of experimental verification of the results. Although the Φ_0 -periodic term in the charge fluctuations may not be easy to access directly, it leads to observable effects in the common electric noise by making it phase sensitive. The phase sensitivity was noticed recently and studied in a different setup [13] with the flux varying periodically in time, $\Phi(t) = \Phi_a \cos \Omega t$, and constant voltage V applied across the conductor. It was found that the noise as function of V at $T \ll eV, \hbar\Omega$ has cusp-like singularities at $V = n\hbar\Omega/e$ with the strengths given by oscillating functions of the ac flux amplitude. The oscillations and peculiar character of the limit $\Omega \rightarrow 0$ indicate the "almost static" nature of the phase sensitivity which was named *non-stationary Aharonov-Bohm effect*. Let us draw

a connection of this effect with the Φ_0 -periodic term in (1). In the setup of Ref. [13] one has the flux $\Phi(t) = -cVt + \Phi_a \cos \Omega t$ applied during all measurement time $2t_0$. Therefore,

$$\left| \int_{-t_0}^{t_0} e^{i\phi(t)+i\omega t} dt \right|^2 = \sum_n J_n^2(2\pi\Phi_a/\Phi_0) 4\pi t_0 \delta(\omega + n\Omega - eV/\hbar) . \quad (19)$$

Integrated over $|\omega| \frac{d\omega}{2\pi}$ Expr.(19) gives charge fluctuations as a sum of cusp-like singularities:

$$\langle\langle Q^2 \rangle\rangle = 2t_0 \sum_n \lambda_n |eV - n\hbar\Omega| , \quad (20)$$

where $\lambda_n = \frac{ge^2}{h} G_1 J_n^2(2\pi\Phi_a/\Phi_0)$. To relate Expr.(20) with the low frequency noise spectral density of Ref. ([13]) one divides it by a factor $2\pi t_0$. Comparison with Expr.(1) makes it clear that the singularities at integer $eV/\hbar\Omega$ are caused by the logarithmic divergence of Expr.(1), while the oscillating dependence on Φ_a is related with the periodic dependence of the first term of Expr.(1) on Φ . Thus both features, singularities and oscillations, arise as elements of the same phenomenon. The property of the singularities (20) to persist as $\Omega \rightarrow 0$ is explained by weak logarithmic dependence of Expr.(1) on the duration τ of the flux switching.

Before we close, let us mention another experimental situation where the phenomena described above may lead to observable effects. The possibility to change flux by a non-integer amount is naturally realized in superconductors, since superconducting flux quantum is $\frac{1}{2}\Phi_0$. Therefore, if a normal conductor is surrounding a superconducting system in which the flux is switching by $\frac{n}{2}\Phi_0$, e.g., due to quantum tunneling, it will distinguish between odd and even n by noise level. In the case when Ohmic dissipation in normal metal is strong, it may significantly suppress the odd flux tunneling rate and lead to tunneling of flux pairs.

In conclusion, we studied charge fluctuations in a system driven by flux varying from one constant value to another. In contrast with the average transmitted charge proportional to the flux change, the mean square of charge fluctuations contains a term distinguishing between integer and non-integer flux change. As a result, the dependence of noise on the flux is non-monotonous and has minima near integer values. The special role of integer flux is put in connection with the binomial statistics picture of charge fluctuations, where the flux quanta are naturally interpreted as discrete attempts to transmit charge.

ACKNOWLEDGMENTS

We are grateful to Gordey Lesovik for the influence he had on this work. Research of L.L. is partly supported by Alfred Sloan fellowship.

REFERENCES

* also at: L.D.Landau Institute for Theoretical Physics, 2, Kosygin str., Moscow 117334, Russia

- [1] P. W. Anderson, Phys.Rev.Lett.,**18**, 1049 (1967)
- [2] P. Nozières, C. T. deDominicis, Phys.Rev., **178**, 1084 (1969)
- [3] G. D. Mahan, Many Particle Physics, Sec. 8.3, (2-nd edition, Plenum Press, 1990)
- [4] L. D. Landau and E. M. Lifshitz, Statistical Physics, Part 1, §125 (Pergamon Press, Oxford, 1980)
- [5] G. B. Lesovik, JETP Letters, **49**, p.594 (1989)
- [6] B. Yurke and G. P. Kochanski, Phys.Rev.**41**, p.8184 (1989)
- [7] M. Büttiker, Phys.Rev.Lett., **65**, p.2901 (1990);
- [8] S.-R. Eric Yang, Solid State Commun.**81**, 375 (1992)
- [9] C. W. J. Beenakker, M. Büttiker, Phys.Rev.B**46**, 1889 (1992)
- [10] Th. Martin and R. Landauer, Phys.Rev.**B45**, 1742 (1992)
- [11] L. S. Levitov, G. B. Lesovik, JETP Letters **58** (3), p.230, (1993)
- [12] R. Landauer, in: Localization, Interaction and Transport Phenomena, eds. B.Kramer, G.Bergmann and Y.Bruynsraede (Springer, Heidelberg, 1985) Vol.**61**, p.38;
see also a review by R. Landauer in: W.van Haeringen and D.Lenstra (eds.), Analogies in Optics and Micro Electronics, pp.243-257, Kluwer Academic Publishers (1990)
- [13] G. B. Lesovik, L. S. Levitov, Noise in an AC biased junction. Non-stationary Aharonov-Bohm effect. (preprint 9311048 at cond-mat@babbage.sissa.it)

FIGURES

FIG. 1. Mesoscopic disordered conductor with ideal leads bent in a loop of length L through which magnetic flux $\Phi(t)$ is applied.